

# CHAT® 150 | CHATAttach™ 150 USB

## Personal/Group Speaker Phones

Speaker phones for individual, small, medium or large group use. The CHAT 150 and CHATAttach 150 USB connect to PCs for rich, full-duplex audio communications and can be used with VoIP softphones, Web collaboration, instant messaging and any other applications requiring two-way audio. A perfect addition to the office or conference room for greatly enhanced collaboration.

**ClearOne**



DELIVERS  
SUPERIOR  
HANDS-FREE  
AUDIO FOR  
PC-BASED  
COLLABORATION  
APPLICATIONS

### APPLICATIONS

- Web Conferencing
  - + IBM Workplace
  - + Microsoft Live Meeting, WebEx
- VoIP Softphones
  - + Avaya, Cisco, Nortel, Mirial
- Internet Telephony
  - + Google Talk, Skype, Vonage
- Instant Messenger
  - + AOL, Microsoft MSN, Yahoo

### ADVANTAGES

- Enable full-duplex speaker phone capabilities on PCs or laptops
- + Connect the CHAT 150 or the CHATAttach 150 to laptops & PCs via USB for hands-free audio for:
  - > VoIP softphones
  - > Instant Messaging audio chats
  - > Web conferences
- Enjoy rich audio playback
  - + Full bandwidth frequency response provides rich audio playback with media players
- Enjoy crisp, clear audio
  - + Advanced ClearOne HDConference™ audio processing technologies deliver remarkably rich, full audio for natural, effortless conversations:
    - > True full duplex performance allows user to listen and speak at the same time without audio cutting in and out
    - > Distributed Echo Cancellation®
    - > Noise cancellation
    - > Advanced automatic level management
- + Three built-in microphones provide full 360-degree coverage up to 8 feet from device
- + Bridge audio from PC applications with audio on telephone for instant 3-way conference bridge

HDConference™

> **CHAT 150 COMPONENTS**



**CHAT 150 Unit**  
Part # 910-156-200



**USB 2.0 Connection Cable**  
Part # 830-156-200



**Quick Start Guide**  
Part # 800-156-202

> **CHATAttach 150 COMPONENTS**

**CHATAttach Packout for the CHAT 150**



**Two CHAT 150 Units**  
Part # 910-156-200



**USB 2.0 Connection Cable**  
Part # 830-156-200



**CHATAttach Cable**  
Part # 830-156-010L



**CHATAttach Power Supply**  
Part # 551-156-200



**CHATAttach Quick Start Guide**  
Part # 800-156-225

**Ready out of the box**

All the components you need to quickly get up and running, including cabling and Quick Start Guide.

**CHATAttach Expansion Cable Packout**



**CHATAttach Cable**  
Part # 830-156-010L




**CHATAttach Power Supply**  
Part # 551-156-200




**CHATAttach Quick Start Guide**  
Part # 800-156-225

> **ROOM APPLICATIONS**

**CHAT 150**



**CHATAttach 150**



**Configuration Software**

Allows users to easily switch between devices; software applies optimized settings to CHAT 150 for each device. Auto-updates from the Web to keep software & CHAT 150 up-to-date with the latest enhancements.

> **SPECIFICATIONS**

**Connections**

USB Connector  
Version 2.0 Compatible  
Type: Mini B Female

Keyed Connector  
Keyed RJ-45 (8 Conductor)

**Controls**

Volume Up  
Volume Down  
Microphone Mute

**Operating System Support**

Windows XP  
Windows Vista  
Windows 7

**Audio**

Speaker  
Bandwidth: 190 Hz - 20 kHz  
Max Output Level: 85 dB SPL @ 1 meter

Microphone  
Bandwidth: 100 Hz - 12 kHz

**Power**

USB-powered  
5 VDC @ 500 mA Maximum

External Power Supply  
100 - 240 VAC Input  
9 VDC @ 560 mA Output

**Environmental**

Operating temperature:  
5 - 40° C (41 - 104° F)

**Mechanical**

CHAT 150 Dimensions (W x D x H):  
7.4" x 7.4" x 1.8"  
(18.8 cm x 18.8 cm x 4.6 cm)

CHAT 150 Weight:  
1.17 lbs (0.53 kg)

**Compliance**

RoHS  
FCC Class A Part 15  
FCC Part 15.19 (A) (3)  
ICES-003  
EU Compliance

**Model Numbers**

**910-156-200**  
**Chat 150 USB**

- Single CHAT 150 and Connecting Cable

**910-156-200-00**  
**CHATAttach 150**

- Two (2) CHAT 150 Devices, Connecting Cables and Power Supply

**910-156-222**

**CHAT 150 Avaya**

- CHAT 150 and Connecting Cable to Avaya Enterprise Phone

**910-156-220**

**CHAT 150 Cisco**

- CHAT 150 and Connecting Cable to Cisco Enterprise Phone

**910-156-230**

**CHAT 150 VC**

- CHAT 150 and Cable to Video Conference System

**Accessory Part Numbers**

**860-156-230L**

**CHAT 150 VC Accessory Kit**

- Includes Video Conferencing Breakout Box, Power Adapter, International Power Clips, RCA Connection Cable, 25' Link Cable

**860-156-222L**

**CHAT 150 Avaya Accessory Kit**

- Includes Breakout Box for 2410, 2420, 4610 and 4621 Telephone Handsets, Power Adapter, International Power Clips, RJ-9/RJ-9 Telephone Cable, 25' Link Cable

**860-156-220L**

**Chat 150 Cisco Accessory Kit**

- Includes Breakout Box for 7940, 7960, and 7970 Telephones, Power Adapter, International Power Clips, RJ-9/RJ-9 Telephone Cable, 25' Link Cable

**910-156-225**

**CHATAttach Expansion Kit**

- Includes Cables, Power Supply and Quick Start Guide to Update Two (2) CHAT 150 Devices to CHATAAttach

> **CLEARONE LOCATIONS**

**Headquarters:**

**Salt Lake City, UT USA**

5225 Wiley Post Way  
Suite 500

Salt Lake City, UT 84116

**Tel:** 801-975-7200

**Toll Free:** 800-945-7730

**Fax:** 801-977-0087

**e-mail:** sales@clearone.com

**Latin America**

**Tel:** 801-974-3621

**e-mail:** global@clearone.com

**EMEA**

**Tel:** 44 (0) 1189 036 053

**e-mail:** global@clearone.com

**APAC**

**Tel:** 801-303-3388

**e-mail:** global@clearone.com

**Technical Support**

**APAC**

**Tel:** 801-283-5936

**e-mail:** tech.support@clearone.com